SN100Ce (SnNi)

 Date
 2021.05.10

 Language
 English

 SDS
 950002



SUMMARY

SN100Ce copper-reduced solder is the replenishment alloy for SN100C solder to keep the solder bath within the process limits.

ALLOY	SN100Ce (SnNi)		
PROCESS			
Leadfree		9	
Leaded		1	
First filling*		1	
Refilling*		9	

*follow Application Note

INDUSTRY APPLICATION		
Standard electronics	9	
Industrial electronics	9	
Hi-Rel electronics (automotive)	8	

PROCESS CAPABILITY	
Wave soldering	9
Selective soldering	8
Dip soldering	8
Wire tinning	4
Process: Ambient	8
Process: N2 partial	8
Process: N2	8
Reduces dross	8
Reduces bridging	8
Improves PTH filling	8
Shiny joint appearance	9

Legend		
Especially made for this purpose	9 - 10	
Generally qualified for this purpose	7 - 8	
Generally usable, but not the best choice		
Generally not usable for this purpose		
Wrong choice	1 - 2	

Check material compatibility with every process change.

Read AN before use.

Read MSDS before use.

PROPERTIES		
WBZ.: Triple X		
SN100Ce		
SnNi		
not compliant		
-		
[°C]	227	
[°C]	227	
[°C]	260 - 320	
	SN' S not co	

*follow Application Note

COMPOSITION				
Tin	[Sn]	Remainder		
Copper	[Cu]	max. 0.2		
Nickel	[Ni]	0.04 - 0.06		
Germanium	[Ge]	0.005 - 0.007		
Silver	[Ag]	max. 0.05		
Aluminium	[AI]	max. 0.001		
Arsenic	[As]	max. 0.03		
Gold	[Au]	max. 0.03		
Bismuth	[Bi]	max. 0.03		
Cadmium	[Cd]	max. 0.002		
Iron	[Fe]	max. 0.02		
Indium	[ln]	max. 0.03		
Lead	[Pb]	max. 0.05		
Antimony	[Sb]	max. 0.05		
Zinc	[Zn]	max. 0.001		

SHAPE AND DIMENSION*				
Ingot	1 kg	LxWxH [mm]	325x28x15	
Ingot with loop	3.7 kg	LxWxH [mm]	540x50/40x20	
	4 kg	LxWxH [mm]	515x50/48x22	
Bar	Rectangle	[mm]	400x10x8	
	Triangular	[mm]	400x10x10	
Pellet		[mm]	12x25	
Solid wire	0	[mm]	1.0 - 6.0	
*-4				

*other dimensions on request

Disclaimer:

The information given in this publication has been worked up to the best of the knowledge of Cobar as well as taking into consideration the applicable laws and regulations. We cannot anticipate all conditions under which this information and our products or the products of other manufacturers in combination with our products may be used. We accept no responsibility for results obtained by the application of this information or the safety and suitability of our products alone or in combination with other products. Users are advised to make their own tests to determine the safety and suitability of each such product combination for their own purposes. Unless otherwise agreed in writing, we sell the products without warranty, and buyers and users assume all responsibility and liability for loss or damage arising from the handling and use of our products, whether used alone or in combination with other products.

